

TP-LINK VR300 GUIDE

FTTN/FTTB



PHYSICAL APPEARANCE



Top pannel



Back pannel


Item	Description
POWER Port	For connecting the modem router to a power socket via the provided power adapter.
ON/OFF Button	The switch for the power. Press it to power on or off the modem router.
RESET Button	Press and hold down for about 2 seconds to reset the modem router into factory default settings.
WPS Button	Press to start a WPS synchronization.
LAN1, LAN2, LAN3, LAN4/WAN Port	For connecting the modem router to your PC or other Ethernet network devices. In wireless router mode, the LAN4/WAN port is used for connecting to a Cable/FTTP/FIXED WIRELESS/HFC/FTTC.
DSL Port	For connecting the modem router to FTTN/FTTB. Connect the to the phone socket via phone cable.
Antennas	Used for wireless data transmission. Position them upright for the best performance.

CONFIGURING YOUR MODEM VIA SETUP WIZARD


To access modem gateway, enter <http://tplinkmodem.net> or <http://192.168.1.1> in the address bar of a web browser.

1. Log in with the account you set for the modem router, otherwise check the default username and password on the sticker of your modem.


Note: Please ensure the password is strong and you memorise it. This will be the password for future logins.



2. Once logged in you will have the option to set up the modem via quick setup (set up wizard). Select the region and time zone as shown in below example. Click **'Next'**.



3. Select 'Other' From the ISP List as shown above. Click '**Next**'.




4. Under '**Internet Setup**' choose the following settings:


For FTTN/FTTB NBN

Select VDSL and PPPoE and type in the username and password provided in your welcome email. Then click '**Next**'.

Example:



5. You can change the WiFi name and password here, otherwise click **'Next'**.



The screenshot shows the TP-Link Quick Setup interface. At the top, there are tabs for 'Quick Setup', 'Basic', and 'Advanced'. A progress bar indicates the current step is 'Wireless Settings', with previous steps being 'Region and Time Zone', 'Internet Setup', and 'Connection Test', and future steps being 'Summary' and 'TP-Link Cloud Service'. The main content area contains the following text and fields:

You can change the wireless network name and password.

2.4GHz Wireless: Enable Wireless Radio

Network Name (SSID):

Password:


5GHz Wireless: Enable Wireless Radio

Network Name (SSID):

Password:

At the bottom right, there are 'Back' and 'Next' buttons.

6. This 'Sorry' message is expected at this stage. Please ignore this message and click **'Next'**.




The screenshot shows the TP-Link Quick Setup interface. At the top, there are tabs for 'Quick Setup', 'Basic', and 'Advanced'. A progress bar indicates the current step is 'Connection Test', with previous steps being 'Region and Time Zone', 'Internet Setup', and 'Wireless Settings', and future steps being 'Summary' and 'TP-Link Cloud Service'. The main content area displays an error message:

 **Sorry!**


Internet not connected. Please reconfigure your parameters. If the problem still exists, please contact your ISP.

Below the message is a 'Reconfig' button. At the bottom right, there are 'Back' and 'Next' buttons.

7. Click **'Finish'**.



8. Again, please ignore this 'Failed' message and click **'Finish'**.




9. If configured correctly, the **'Internet Status'** will now say **'Connected'**!

Internet

Internet Status:	Connected
Connection Type:	PPPoE
IP Address:	14.137.222.93
DNS Server:	111.220.1.1 111.220.2.2
Gateway:	202.138.24.236


MANUALLY SETUP AN INTERNET CONNECTION

1. Once logged in, go to **Basic > Internet page**. Select **'Other'** in ISP, and related information will be automatically filled in.
2. Then enter the information needed (username and password). Then click **'Save'**.
3. Select PPPoE for the connection type. Enter the username and password provided in your email from us, and click **'Save'** to apply the changes.



The screenshot shows the TP-Link Basic Internet Connection Setup page. The 'Basic' tab is selected. In the left sidebar, 'Internet' is highlighted. The main content area is titled 'Internet Connection Setup'. A dropdown menu for 'ISP List' is set to 'Other'. Below it, the 'VPI' field is set to '0' and the 'VCI' field is set to '38'. The 'Connection Type' dropdown is set to 'PPPoE'. There are input fields for 'Username' and 'Password'. A green 'Save' button is located at the bottom right of the form.

For FTTN/FTTB customers: Ensure that the 'Operation Mode' is set to 'DSL Modem Router Mode'.



The screenshot shows the TP-Link Advanced Operation Mode page. The 'Advanced' tab is selected. In the left sidebar, 'Operation Mode' is highlighted. The main content area is titled 'Operation Mode'. Below the title, it says 'Please select an operation mode:'. There are two radio button options: 'DSL Modem Router Mode' (which is selected) and 'Wireless Router Mode'. A green 'Save' button is located at the bottom right of the form.